




## 4Port Compact Auto KVM Switch Box **KVM-04**



### Feature

The switch box can save space and installation cost as it allows the user to control four PC's from just a single console set (a mouse, a keyboard and a monitor).

#### ■ Easily switches between two PC's via a button, provides hot key support

Simply press the Select button on the upper side of the product to switch over to three additional PC's. The KVM-04 is equipped with four PC ports and allows the user to access four PC's using just one console set. The KVM-04 also supports hot key sequence, a feature that lets the user switch between four PC's and/or perform auto PC scan from a keyboard directly attached to the switch box.

#### ■ Auto scan mode automatically switches between the attached PC's

When this mode is enabled, the KVM-04 automatically switches between the attached PC's every five seconds. This feature is particularly useful when the user needs to continuously monitor multiple systems (ex. four publicly accessible servers) that have been attached to the product.

#### ■ Supports hot plug (Keyboard/ Mouse)

Since the KVM-04 supports hot plug, the user can attach or remove the keyboard or mouse while the computer is up and running.

#### ■ Automatically saves keyboard configuration

The switch box automatically saves the PC-specific keyboard configuration to the attached PC itself. The saved configuration is automatically restored when the PC boots.

#### ■ Supports high resolution

The KVM-04 supports high VGA resolution of 1,920 X 1,400 (max) as well as high bandwidth 200MHz.

#### ■ KVM Cable

Option



## Specifications

<b>Product Model Number</b>	<b>KVM-04</b>	
<b>Number of PC's Supported</b>	4	
<ul style="list-style-type: none"> <li>• Interfaces (KVM)</li> <li>• Interfaces (PC)</li> </ul>	<b>Keyboard</b>	PS/2 keyboard 6pin mini Din (female)
	<b>Mouse</b>	PS/2 mouse 6pin mini Din (female)
	<b>VGA (Monitor)</b>	Mini D-Sub 15pin (female)
<b>Supplied KVM Cable Interface</b>	<b>Keyboard</b>	PS/2 keyboard 6pin mini Din (male)
	<b>Mouse</b>	PS/2 mouse 6pin mini Din (male)
	<b>VGA (Monitor)</b>	Mini D-Sub 15pin (male)
<b>Switching Method</b>	Select button / hot key sequence via keyboard	
<b>LED Indicators</b>	Power On LED: Illuminates when the power is turned on On Line LED: Indicates the PC that is currently selected	
<b>Power Input</b>	-Directly draws power from a PS/2 keyboard port on the attached PC (DC +5V) -AC Power Adapter (DC5-9V, 500mA -1A) * * KVM-04 only	
<b>Operating Environmental Requirements</b>	Temperatures: 0-40 degrees Celsius Humidities: 35-85% (non-condensing)	
<b>Dimensions/Weight (Main Body Only)</b>	200(W) x 44(H) x 98(D)mm/720g	
<b>EMI</b>	FCC Class A,CE	
<b>Supported OSes</b>	Windows 95/98/98SE/2000/Me/XP,Linux,FreeBSD	
<b>System Requirements</b>	IBM PC/AT compatible equipped with a PS/2 keyboard connector, a PS/2 mouse connector and D-Sub 15pin VGA output support * Notebook PC's are not supported	
<b>Package Contents</b>	KVM-04 (metal case), User's Manual, 1.8m KVM Cable x 2, 1.2m KVM Cable x 2, AC Adapter	

▼ Product View

